

APF02 Easywave "Fon Alarm" set including wristband transmitter

With an Easywave transmitter, you can transmit a signal to the "Easywave Fon Alarm" telephone at the touch of a button. The telephone then dials three pre-programmed telephone numbers one after the other. If the recipient confirms the call by pressing the "0" button, a conversation can be carried out for three minutes using the integrated hands-free equipment. The telephone provides persons in need of care with an ideal means of calling for help in "emergency situations".

Along with the obligatory wristband or necklace transmitters, wall transmitters or fall mats, for example, can also be used. A total of eight transmission codes can be programmed into the telephone.



APF02E5000A01-00K

Technical specifications

| | |
|--------------|---|
| Coding | Easywave 8 transmitters can be programmed. |
| Frequency | 868.30 MHz |
| Channels | 1 |
| Power supply | 9 V DC (AC adapter included) |
| Connection | F/RJ11 analog telephone plug |
| Dimensions | 175 x 205 x 80 mm |
| Color | silver |

Telephone details

| |
|---|
| Telephone with large buttons, backlit display and clock |
| Selectable menu language (German, English, French, Italian) |
| Visual call indicator ("telephone ringing" LED) |
| Adjustable handset volume, tone control is possible |
| Compatible with hearing aids |
| Adjustable ringtone volume |
| 30 phone book entries are possible |
| Voice output when button is pressed |
| Hands-free function |
| Caller number (CLIP) and call history (64 calls) display |

Scope of delivery

- "Fon Alarm" telephone
- AC adapter, wall holder
- RJ11/RJ11 telephone cable (length 2,15 m)
- F/RJ11 telephone plug
- 4 AA 1.5 V batteries
- RT26 wristband transmitter including battery
- Operating manual

Models

| Product numbers | Description |
|-------------------|---|
| APF02E5000A01-00K | Easywave "Fon Alarm" telephone including RT26 wristband transmitter |