

RGD02 DALI gateway

The RGD02 Easywave DALI gateway enables control of up to 8 different DALI devices from a total of 32 Easywave transmitters. Each DALI device can be assigned its own function.

The programmed transmitters can be individually named and assigned to the previously defined functions / addressing modes. This information is stored directly on the device and is available if changes are made at a later stage.

To configure the RGD02, the start-up cable, which is available separately, a Windows PC / laptop as well as the "RGD02_Configurator" software are required.



RGD02E5008-01-23K

Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30 MHz
Channels	8
Range	typically 150 m in good free-field conditions
Power supply	DALI bus voltage 11.5 to 20.5 V DC
Operating modes	ON/OFF (1-button operation) ON/OFF (2-button operation) DIMMING (1-button operation) DIMMING (2-button operation) DEADMAN (1-button operation) go to scene jump through scenes fixed dimming value
Power consumption	21 mA
Operating temperature	-20 °C to +60 °C
Dimensions	46 x 46 x 25 mm

Scope of delivery

- DALI gateway
- Operating manual

Accessories (optional)

RGD-ACC-01-00K	Start-up cable, length 3 m and software CD
----------------	--

Models

Product numbers	Description
RGD02E5008-01-23K	DALI gateway 8-channel