



Transmit



Receive



Decode



Control

Hand Transmitter RT29

The Hand Transmitter RT29 offers a large variety of applications with up to 10 channels.

Depending on the model it can be used for different functions:

10-channel-version:

switching up to 10 electrical consumers with 1-button-operation

5-channel-version:

switching up to 5 electrical consumers with 2-button-operation.

4-channel-version:

controlling 2 shutters (UP/STOP/DOWN) and switching 2 electrical consumers with 2-button-operation.



RT29-5004E-01

Technical Details




Coding	factory coding with Easywave Telegram
Channels	4, 5 or 10
Range	up to 150 m under favourable open field conditions
Power Supply	1x 3V battery, CR2032
Operation Indicator	LED
Control	transmission lasts for as long as button is pressed (but max. 36 s)
Operation Modes	depending on the receiver; see model
Degree of Protection	IP54
Operating Temperatur	-20 °C to +60 °C
Dimensions	110 x 38 x 14 mm
Weight	37 g (including battery)

Scope of Delivery

- Hand Transmitter incl. battery
- Mounting Plate
- Mounting Accessories
- Operating Manual

Accessories (optional)

- Battery ACC-BAT-05



Models

Product Key	RT29-5004E-01	RT29-5005E-01	RT29-5010E-01
Frequency	868.30 MHz	868.30 MHz	868.30 MHz
Description	Hand Transmitter	Hand Transmitter	Hand Transmitter
Control	3-button-control or 2-button-control	2-button-control	1-button-control
Operation Modes	2x UP/STOP/DOWN and 2x ON/OFF	5x ON/OFF	10x Pulse