

RT39 Display hand transmitter with timer

The RT39 hand transmitter serves to control Easywave radio receivers according to a timer and to operate roller shutters or awnings automatically.

The hand transmitter has 30 radio channels through which it sends the Easywave code. In this way, up to 30 Easywave radio receivers can be controlled individually or simultaneously. When controlling the receivers simultaneously, the radio channels may be divided into up to 9 groups.

It is also possible to program a total of 99 switching times. The programming remains stored even if the power supply is interrupted.



RT39E5023-01-01K

Technical specifications

Coding	factory coding with Easywave telegram
Frequency	868.30 MHz
Channels	30
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2430
Operating indicator	display
Operation	see operating manual
Function	depends on the receiver (see models)
Operating temperature	0 °C to +50 °C
Dimensions	52 x 120 x 13 mm
Weight	74 g (including CR2430 battery)
Color	white similar to RAL 9003

Scope of delivery

- Display hand transmitter including battery
- Operating manual

Models

Product numbers	Description	Function
RT39E5023-01-01K	Display hand transmitter 30-channel with timer, white	30x UP/STOP/DOWN or 30x ON/OFF