

RTS08 Radio wall switch

The RTS08 wall switch is designed to be surface-mounted inside dry buildings.

The switch can be fitted to standard switch boxes or attached or screwed directly to a wall.

The RTS08 is generally used as a light switch to turn one or two lights ON or OFF with a 2-button operation.



RTS08E5002-01-02K


Technical specifications

Coding	factory coding with Easywave telegram
Frequency	868.30 MHz
Channels	1, 2 or 4
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2032
Operation	transmission lasts as long as the button is pressed (maximum 36 seconds)
Function	depends on the receiver (see models)
Operating temperature	-20 °C to +60 °C
Dimensions	80 x 80 x 10 mm
Weight	47 g (including battery)
Color	white similar to RAL 9003


Scope of delivery

- Wall switch including battery
- Mounting kit
- Operating manual


Models



RTS08E5001-01-02K
1x OFF



RTS08E5002-01-02K
1x ON/OFF or
2x PULSE



RTS08E5004-01-02K
2x ON/OFF or
4x PULSE

Models

Product numbers	Description	Function
RTS08E5001-01-02K	Radio wall switch 1-channel, white	1x OFF
RTS08E5002-01-02K	Radio wall switch 2-channel, white	1x ON/OFF or 2x PULSE
RTS08E5004-01-02K	Radio wall switch 4-channel, white	2x ON/OFF or 4x PULSE