

## RTS14 Radio wall switch

The RTS14 wall switch is designed to be surface-mounted inside dry buildings.

The switch can be fitted to standard switch boxes or attached/screwed directly to a wall.

Depending on the model and the connected Easywave receiver, the RTS14 can be used to switch electrical devices on or off with a 1- or 2-button operation as well as to control roller shutters/awnings.




RTS14E5003-01-02K


### Technical specifications

Coding	factory coding with Easywave telegram
Frequency	868.30 MHz
Channels	2, 3 or 6
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2032
Operation	transmission lasts as long as the button is pressed (maximum 36 seconds)
Function	depends on the receiver (see models)
Operating temperature	-20 °C to +60 °C
Dimensions	80 x 80 x 10 mm
Weight	47 g (including battery)
Color	white similar to RAL 9003


### Models



RTS14E5002-01-02K  
2x UP/STOP/DOWN



RTS14E5003-01-02K  
3x ON/OFF



RTS14E-5006-01-02K  
6x PULSE

### Scope of delivery

- Wall switch
- Battery
- Mounting kit
- Operating manual

### Models

Product numbers	Description	Function
RTS14E5002-01-02K	Radio wall switch 2-channel, white	2x UP/STOP/DOWN
RTS14E5003-01-02K	Radio wall switch 3-channel, white	3x ON/OFF
RTS14E5006-01-02K	Radio wall switch 6-channel, white	6x PULSE