

RT42 Handsender

PULSE

The RT42 hand transmitter is a wireless transmitter which transmits the secwave code at the push of a button, and activates the secwave wireless receiver according to the selected mode.

The transmitter has a battery control function which checks the battery capacity. If the battery capacity is low, the LED flashes after the transmitter button is released.



Technical specifications

Coding	secwave AES 128-bit encryption Not compatible with Easywave products!
Frequency	868.30 MHz
Channels	4
Range	typically 150 m in good free-field conditions
Power supply	1x 3V-battery, CR2032
Operating indicator	LED
Operating modes	4x PULSE
Operation	transmission starts as soon as button is pressed
Operating temperature	-20 °C to +60 °C
Dimensions (W/L/H)	37/61.5/10.7 mm
Weight	30 g (including battery)
Color	black similar RAL 9005

Scope of delivery

- Hand transmitter
incl. battery
- Key protection
- Operating manual

Accessories (optional)

RT42-ACC-01-21U	Key protection RT42/RT43 black similar RAL9005
-----------------	---



Models

Product number	Description
RT42S5004A01-21K	Hand transmitter, secwave, 4x PULSE, metal bracket, black